

## SET GROUP HUNTING

Group Hunting (Internal) group means that a number of extensions are assigned a common call number. When this number is called one of the extensions (members) is selected. The call is signaled on the telephone of the selected member. The call will be queued if no free member exists.

### LOG IN TO PM

**Do as follows:**

1. Open **Provisioning Manager (PM)**. The start page is displayed.
2. Type the **User name** in the field **User**.
3. Type the **Password** in the field **Password**.
4. Click **Login**. The main page is displayed.

## SET GROUP HUNTING

**Do as follows:**

5. Select **System, Subsystem**, and then click on the link for the **Telephony system**. A **Manager Telephony System** page is displayed.
1. Select **Telephony**, and then **Groups**. A menu to the left is displayed.
2. Select **Hunt Group**. The **Hunt Group** page is displayed.
3. Click **Add**. The **Hunt Group - Add - Step 1 / 3** is displayed.
4. Select an interval from the list **Available Directory Number Intervals**.
5. Click **Next**. The **Hunt Group - Add - Step 2 / 3** is displayed.


## ADD GROUP HUNTING INFORMATION

**Do as follows:**

1. Select a number from the list **Direct Number**.
2. Select an option from the list **Direct In-dialing**.
3. Select an option from the list **Display of Called Number**.
4. If required select options from the list:
  - **Music on Wait**
  - **Allow Collect Call**
  - **Permit Automatic Extending**
5. Select **15** from the list **Traffic Connection Class**.
6. Select an option from the lists:
  - **Member Selection Or**
  - **Queue Internal Calls**
  - **Diversion**
  - **Diversion Number**
7. Click **Next**. The **Hunt Group - Add - Step 3 / 3** is displayed.
8. Type the first name in the field **First Name**.
9. Type the last name in the field **Last Name**.
10. Click **Apply**. An information notice if the operation is displayed.
11. Click **Done**.

## SELECT GROUP HUNTING MEMBERS

**Do as follows:**

1. Select **System, Subsystem**, and then click on the link for the **Telephony system**. A **Manager Telephony System** page is displayed.
2. Select **Telephony**, and then **Groups**. A menu to the left is displayed.
3. Select **Hunt Group Member**. The page **Hunt Group Member** is displayed.
4. Select the group you created before, and click **Change**, . The **Hunt Group Members** page is displayed.
5. Type one or more extension number, separated with a comma.
6. Click **Apply**. An information notice of the operation is displayed.
7. Click **Done**.